

[illegible]

5/9
A

1. A method for determining whether a Boolean function is equivalent to a Boolean constant within a given subset of the input space, comprising the steps of:
- receiving said Boolean function, said Boolean constant and said given subset of the input space;
 - dividing said given subset of the input space into a set of a plurality of smaller subsets of the input space, whereby the conclusion is positive if said Boolean function is equivalent to said Boolean constant within every member of said plurality of smaller subsets of the input space.
2. A method for determining whether a Boolean function is equivalent to a Boolean constant within a given subset of the input space, as in claim 1 further comprising the step of:
- determining whether said given subset of the input space is a cube;
 - simplifying, if said given subset of the input space is a cube, said Boolean function with substituting the input variables in said Boolean function with the constants according to the definition of said cube, whereby the conclusion is positive if the simplification result is said Boolean constant, and the conclusion is negative if the simplification result is a Boolean constant other than said Boolean constant.

6. A method for determining whether a Boolean function is equivalent to a Boolean constant within a given subset of the input space, as in claim 5 further comprising the step of:

repeating the dividing step and the simplifying step if the simplification result is not a Boolean constant, whereby said cube is smaller and the simplification result will eventually be a Boolean constant when said cube is small enough.

7. A method for determining whether a Boolean function is equivalent to a Boolean constant within a given subset of the input space, as in claim 4 wherein said given subset of the input space is represented as a first range of binary integers.

8. A method for determining whether a Boolean function is equivalent to a Boolean constant within a given subset of the input space, as in claim 7 wherein said set of a plurality of smaller subsets of the input space has only two members: said cube which is represented as a second range of binary integers, and a second member which is represented as a third range of binary integers, whereby said third range of binary integers is divided repeatedly into cubes and such divisions do not need to all complete if the negative conclusion is given for any of these cubes.

9. A method for determining whether a Boolean function is equivalent to a Boolean constant within a given subset of the input space, as in claim 8 further comprising the step of:

001220-2292560
R

replacing said given subset of the input space, represented by said first range of binary integers, with said second member of said set of a plurality of smaller subsets of the input space, represented by said third range of binary integers, after finishing all steps related to said cube and said second range of binary integers which represents said cube, whereby said given subset of the input space become smaller and smaller and whether said Boolean function is equivalent to said Boolean constant within said given subset of the input space can be determined using simplification when said given subset of the input space eventually becomes a cube.

10. A method for determining whether a Boolean function is equivalent to a Boolean constant within a given subset of the input space, as in claim 9 further comprising the step of:

shifting a boundary of said third range of binary integers before the replacing step if the corresponding boundary of said first range of binary integers is shifted, whereby a boundary of said first range of binary integers can shift dynamically.

11. A method for determining whether a Boolean function is equivalent to a Boolean constant within a given subset of the input space, as in claim 4 further comprising the step of:

substituting the input variables in said Boolean function with Boolean constants according to the definition of said cube, whereby any tautology checking method can be used to process the Boolean function resulted from the substitution.

13. A method for determining whether a Boolean function is equivalent to a Boolean constant within a given subset of the input space, as in claim 12 wherein said set of a plurality of smaller subsets of the input space has only two members: said cube which is represented as a second range of binary integers, and a second member which is represented as a third range of binary integers, whereby said third range of binary integers is divided repeatedly into cubes and such divisions do not need to all complete if the negative conclusion is given for any of these cubes.

replacing said given subset of the input space, represented by said first range of binary integers, with said second member of said set of a plurality of smaller subsets of the input space, represented by said third range of binary integers, after finishing all steps related to said cube and said second range of binary integers which represents said cube, whereby said given subset of the input space become smaller and smaller and whether said Boolean function is equivalent to said Boolean

15. A method for determining whether a Boolean function is equivalent to a Boolean constant within a given subset of the input space, as in claim 14 further comprising the step of:

16. A method for determining whether a Boolean function is equivalent to a Boolean constant within a given subset of the input space, as in claim 1 further comprising the step of:

17. A method for determining whether a Boolean function is equivalent to a Boolean constant within a given subset of the input space, as in claim 1 further comprising the step of:

starting a process for each member of said set of a plurality of smaller
subsets of the input space determining whether said Boolean function is equivalent
to said Boolean constant within said member of said set of a plurality of smaller
subsets of the input space, whereby these processes can run on the same computer
or on several computers, at the same time or at different times.